

ECODESIGN INFORMATION

Applies to non-residential ventilation units (NRVU)

According to Regulation EU No 1253/2014 of the European Commission, implementing Directive 2009/125/CE of European Parliament

SODECA, S.L.U.

www.sodeca.com

| | | | | % | m³/s | kW | W/m³/s | m/s | Pa | Pa | Pa | % | % | % | | dBA | |
|----------------------------|------------|----------------|------|---|-------|--------|--------|-------|-----|----|----|------|-----|----------------|----------------|-----|------|
| CJTX-C-22/22-3-2V-F-400 | NRVU / UVU | Variable speed | None | | 2.346 | 1.268 | | 5.00 | 235 | | | 40.1 | 0.2 | Not applicable | Not applicable | 82 | 2018 |
| CJTX-C-22/22-4-F-400 IE3 | NRVU / UVU | Variable speed | None | | 3.572 | 2.058 | | 7.62 | 268 | | | 48.1 | 0.2 | Not applicable | Not applicable | 85 | 2018 |
| CJTX-C-22/22-5.5-F-400 IE3 | NRVU / UVU | Variable speed | None | | 3.830 | 2.533 | | 8.17 | 316 | | | 49.2 | 0.1 | Not applicable | Not applicable | 86 | 2018 |
| CJTX-C-22/22-7.5-F-400 IE3 | NRVU / UVU | Variable speed | None | | 4.240 | 3.375 | | 9.04 | 394 | | | 50.8 | 0.1 | Not applicable | Not applicable | 89 | 2018 |
| CJTX-C-22/22-10-F-400 IE3 | NRVU / UVU | Variable speed | None | | 4.533 | 4.464 | | 9.67 | 505 | | | 51.3 | 0.1 | Not applicable | Not applicable | 91 | 2018 |
| CJTX-C-22/22-15-F-400 IE3 | NRVU / UVU | Variable speed | None | | 4.736 | 6.003 | | 10.10 | 673 | | | 51.3 | 0.1 | Not applicable | Not applicable | 94 | 2018 |
| CJTX-C-22/22-20-F-400 IE3 | NRVU / UVU | Variable speed | None | | 4.800 | 6.738 | | 10.23 | 755 | | | 51.3 | 0.1 | Not applicable | Not applicable | 95 | 2018 |
| CJTX-C-25/25-3-F-400 IE3 | NRVU / UVU | Variable speed | None | | 3.933 | 1.450 | | 6.29 | 163 | | | 46.2 | 0.2 | Not applicable | Not applicable | 82 | 2018 |
| CJTX-C-25/25-4-F-400 IE3 | NRVU / UVU | Variable speed | None | | 4.240 | 1.906 | | 6.78 | 207 | | | 47.1 | 0.2 | Not applicable | Not applicable | 85 | 2018 |
| CJTX-C-25/25-5.5-F-400 IE3 | NRVU / UVU | Variable speed | None | | 4.567 | 2.447 | | 7.31 | 255 | | | 48.2 | 0.2 | Not applicable | Not applicable | 87 | 2018 |
| CJTX-C-25/25-7.5-F-400 IE3 | NRVU / UVU | Variable speed | None | | 5.050 | 3.276 | | 8.08 | 320 | | | 49.8 | 0.1 | Not applicable | Not applicable | 89 | 2018 |
| CJTX-C-25/25-10-F-400 IE3 | NRVU / UVU | Variable speed | None | | 2.528 | 2.292 | | 4.04 | 427 | | | 50.3 | 0.3 | Not applicable | Not applicable | 91 | 2018 |
| CJTX-C-25/25-15-F-400 IE3 | NRVU / UVU | Variable speed | None | | 3.210 | 3.417 | | 5.14 | 528 | | | 50.3 | 0.2 | Not applicable | Not applicable | 93 | 2018 |
| CJTX-C-25/25-20-F-400 IE3 | NRVU / UVU | Variable speed | None | | 4.349 | 5.250 | | 6.96 | 631 | | | 50.3 | 0.2 | Not applicable | Not applicable | 96 | 2018 |
| CJTX-C-30/28-3-F-400 IE3 | NRVU / UVU | Variable speed | None | | 5.530 | 1.761 | | 6.53 | 145 | | | 52.8 | 0.2 | Not applicable | Not applicable | 84 | 2018 |
| CJTX-C-30/28-3-2V-F-400 | NRVU / UVU | Variable speed | None | | 4.334 | 1.491 | | 5.12 | 153 | | | 44.9 | 0.2 | Not applicable | Not applicable | 84 | 2018 |
| CJTX-C-30/28-4-F-400 IE3 | NRVU / UVU | Variable speed | None | | 6.050 | 2.347 | | 7.14 | 183 | | | 53.9 | 0.2 | Not applicable | Not applicable | 86 | 2018 |
| CJTX-C-30/28-4-2V-F-400 | NRVU / UVU | Variable speed | None | | 4.351 | 1.841 | | 5.14 | 194 | | | 44.7 | 0.2 | Not applicable | Not applicable | 86 | 2018 |
| CJTX-C-30/28-5.5-F-400 IE3 | NRVU / UVU | Variable speed | None | | 6.940 | 3.798 | | 8.19 | 275 | | | 55.1 | 0.1 | Not applicable | Not applicable | 90 | 2018 |
| CJTX-C-30/28-5.5-2V-F-400 | NRVU / UVU | Variable speed | None | | 5.416 | 3.145 | | 6.39 | 285 | | | 48.2 | 0.2 | Not applicable | Not applicable | 90 | 2018 |
| CJTX-C-30/28-7.5-F-400 IE3 | NRVU / UVU | Variable speed | None | | 7.489 | 4.480 | | 8.84 | 307 | | | 56.9 | 0.1 | Not applicable | Not applicable | 92 | 2018 |
| CJTX-C-30/28-7.5-2V-F-400 | NRVU / UVU | Variable speed | None | | 6.309 | 3.957 | | 7.45 | 317 | | | 51.2 | 0.1 | Not applicable | Not applicable | 92 | 2018 |
| CJTX-C-30/28-10-F-400 IE3 | NRVU / UVU | Variable speed | None | | 8.170 | 6.171 | | 9.65 | 402 | | | 57.5 | 0.1 | Not applicable | Not applicable | 94 | 2018 |
| CJTX-C-30/28-10-2V-F-400 | NRVU / UVU | Variable speed | None | | 6.514 | 5.177 | | 7.69 | 415 | | | 51.2 | 0.1 | Not applicable | Not applicable | 94 | 2018 |
| CJTX-C-30/28-15-F-400 IE3 | NRVU / UVU | Variable speed | None | | 8.827 | 8.896 | | 10.42 | 560 | | | 57.5 | 0.1 | Not applicable | Not applicable | 98 | 2018 |
| CJTX-C-30/28-15-2V-F-400 | NRVU / UVU | Variable speed | None | | 7.595 | 7.882 | | 8.97 | 568 | | | 53.7 | 0.1 | Not applicable | Not applicable | 98 | 2018 |
| CJTX-C-30/28-20-F-400 IE3 | NRVU / UVU | Variable speed | None | | 9.124 | 10.645 | | 10.77 | 661 | | | 57.5 | 0.1 | Not applicable | Not applicable | 100 | 2018 |
| CJTX-C-30/28-20-2V-F-400 | NRVU / UVU | Variable speed | None | | 7.328 | 8.865 | | 8.65 | 672 | | | 53.1 | 0.1 | Not applicable | Not applicable | 100 | 2018 |
| CJTX-C-30/28-25-F-400 IE3 | NRVU / UVU | Variable speed | None | | 9.534 | 12.271 | | 11.26 | 740 | | | 58.1 | 0.1 | Not applicable | Not applicable | 101 | 2018 |
| CJTX-C-30/28-25-2V-F-400 | NRVU / UVU | Variable speed | None | | 9.534 | 12.271 | | 11.26 | 740 | | | 58.1 | 0.1 | Not applicable | Not applicable | 101 | 2018 |
| CJTX-C-7/7#-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-7/7#-2V-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-9/9#-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-9/9#-2V-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-10/10#-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-10/10#-2V-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-12/12#-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-12/12#-2V-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-15/15#-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-15/15#-2V-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-18/18#-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-18/18#-2V-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-20/20#-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-20/20#-2V-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-22/22#-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-22/22#-2V-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-25/25#-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-25/25#-2V-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-30/28#-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |
| CJTX-C-30/28#-2V-F-400 | NRVU / UVU | Variable speed | None | | 0.000 | 0.000 | | 0.00 | | | | 0.0 | | Not applicable | Not applicable | | 2018 |